

## POWERMAG™ FEATURES

### ELECTROMAGNETIC LOCKS:

- Strong holding force of 600 and 1200 lb. models
- Provides worry-free egress in any emergency as soon as the power is cut off
- Perfect for both single and double doors and even sliding doors
- Locks can be installed in under one hour with just four easy steps
- With no moving parts, there is little maintenance and virtually no erosion
- Low voltage (12 or 24VDC), including field-selectable models
- Double door models with 1200lb. locking per side (PM1200SLB1 and -40)
- Low current draw (200mA to 425mA current)
- Choice of US28 or US40 finish (most models)

## POWERSTRIKE™ FEATURES

### ELECTRIC STRIKES:

- For wood, aluminum & hollow metal jams
- Fail-Secure: Normally locked
- Reversible: Non-handed
- Keeper depth: 5/8"
- Strike Opening: 3/4" x 1 3/8"
- Tamper Resistance: up to 1000 lbs.
- Durability: Min. 500,000 cycles
- Rating: 12VDC, 218mA, 55 Ohms, 24VDC, 215mA, 110 Ohms
- Temperature Resistance: 165°F to -20°F

## POWEREXIT™ FEATURES

### REQUEST-TO-EXIT PUSH BUTTONS:

- PowerExit Push Buttons come in five models, with and without illuminated buttons
- All models have solid aluminum anodized finish US28
- Sizes: 3" x 4 3/8" x 1/4" and 1 5/8" x 4 3/8" x 1/4"
- Back Depth: 1 1/4" and 1 7/8"
- Switch Rating: 250V AC 5A
- Momentary Action

## ORDERING INFORMATION

**PowerMags:** PM600 - 600lb., US28, PM600B1 - 600lb., 12/24 VDC Field-Selectable, US28, PM600L - 600lb., LED and Status Indicator, US28, PM1200 - 1200lb., US28, PM1200-40 - Like PM1200, in US40, PM1200S - 1200lb., Status Indicator, US28, PM1200SL - 1200lb., LED and Status Indicator, US28, PM1200SL-40 - Like PM1200SL, in US40, PM1200SLB1 - 1200lb. each for dual doors, LED and Status Indicator, 12/24 VDC Field-Selectable, US28, PM1200SLB1-40 - Like PM1200SLB1, in US40

**PowerMag Accessories:** Armature Housings: PMA-ARMH1, PMA-ARMH2 • Angle Brackets: PMA-ANGL1, PMA-ANGL2 (Adjustable), PMA-ANGL3 (Adjustable) • Z-Brackets: PMA-Z1 (For PM600 12-24; PM600LED), PMA-Z2 (For PM1200; PM1200S; PM1200SL); PM1200SLLED 12-24) • Filler Plates: PMA-FILL1, 5/8", PMA-FILL2, 1/2"

**PowerStrikes:** PS1, PS2, PS3, PS4

**PowerExits:** PE1, PE2, PE2S, PE3, PE3S

**Accessories:** Power Supplies: AL-PS1A, -PS3A, -PS6A

Key Switches: AL-KM0, AL-KM2

**ALARM LOCK SYSTEMS, Inc.** • A Division of the NAPCO Security Group

345 Bayview Avenue • Amityville, NY • 11701 • USA

**In North America:** 1-800-ALA-LOCK • Fax: 631-789-3383 • +631-789-4871

**In Europe:** +44 (0) 1924 24248 • Fax: +44 (0) 1925 24249

• [www.alarmlock.com](http://www.alarmlock.com)



**ALARM LOCK**

PowerMags, PowerStrikes, PowerExits